

# Ei184

## Heat Alarm



- Heat sensor - responds to heat build-up from large flaming fires (triggers at 58°C)
- 12-24V DC powered with 9V Alkaline battery back-up
- Easi-fit base for quick and simple installation
- Kitemarked to BS 5446-2:2003
- 5 year guarantee



Kitchen



Garage

## Description

The Ei184 Heat Alarm runs on a 12V to 24V DC power and has a 9V Alkaline battery back-up. The alarm has a pair of built-in Volt free relay contacts (i.e. can be used to switch into a burglar panel)

## Technical

<b>Sensor Type</b>	Heat	<b>Indicators</b>	Green - Power / Red - Alarm or fault
<b>Supply Voltage (V)</b>	10-30	<b>Voltage Type</b>	DC
<b>Battery Type</b>	Alkaline PP3		

## Dimensions & Weights

<b>Depth (mm)</b>	95	<b>Height (mm)</b>	155
<b>Width (mm)</b>	150	<b>Product weight (kg)</b>	0.318
<b>Packaged weight (kg)</b>	0.38		

## Approvals & Warranty

<b>Certification/Approvals</b>	BS 5446-2:3003	<b>Warranty</b>	5 year warranty
<b>EAN Number</b>	5099383003109		

## Environmental

<b>Humidity Range (%)</b>	0-90	<b>Temperature Range (°C)</b>	-10 to 40
---------------------------	------	-------------------------------	-----------