

# Ei168RC

## RadioLINK Base



- Add this to a 140RC Series alarm for RadioLINK wireless interconnection
- Mains powered with Rechargeable Lithium Back-up
- Eliminates tricky wiring runs
- Compatible with other Aico wireless interconnection products
- 5 year guarantee



## Description

The Ei168RC RadioLINK Base is an easi-fit mounting plate with built-in RadioLINK. It provides wireless interconnection between 140RC Series alarms, i.e. when one alarm is triggered, all alarms in the system sound

## Technical

<b>RF Frequency (MHz)</b>	868.499	<b>RF Range (m)</b>	>100 in free air
<b>Indicators</b>	Blue - RF transmission	<b>Supply Voltage (V)</b>	230
<b>Voltage Type</b>	AC	<b>Battery Type</b>	Lithium rechargeable
<b>Power Consumption (W)</b>	2.4	<b>Technologies</b>	RadioLINK

## Dimensions & Weights

<b>Depth (mm)</b>	43	<b>Height (mm)</b>	154
<b>Width (mm)</b>	153	<b>Product weight (kg)</b>	0.176
<b>Packaged weight (kg)</b>	0.232		

## Approvals & Warranty

<b>Warranty</b>	5 year warranty	<b>EAN Number</b>	5099383004281
-----------------	-----------------	-------------------	---------------

## Environmental

<b>Humidity Range (%)</b>	15-95	<b>Temperature Range (°C)</b>	-10 to 40
---------------------------	-------	-------------------------------	-----------